

COMMENTS:



DIMENSIONS AND TOLERANCES PER ASME Y14.5M-1994
SURFACE TEXTURE PER ANSI/ASME B46 1 -1985

Projection



UNLESS OTHERWISE SPECIFIED:

- ALL DIMENSIONS IN mm
- PRODUCT DIMENSIONS SUBJECT TO CHANGE



- Step 1: Carefully Align and Place Flyway onto Mounting Plate (M1)
- Step 2: Insert 2x 4mm Dowel Pins (P1 & P2)
- Step 3: Install 2x M8 Screws (S1 & S2)
- Step 4: Remove 2x 4mm Dowel Pins (P1 & P2)
- Step 5: Install 2x M8 Screws (S3 & S4)

PROPRIETARY AND CONFIDENTIAL
THE INFORMATION CONTAINED IN THIS
DRAWING IS THE SOLE PROPERTY OF
PLANAR MOTOR INCORPORATED AND
ANY REPRODUCTION IN PART OR AS A
WHOLE WITHOUT THE WRITTEN PERMISSION
OF PLANAR MOTOR INCORPORATED
IS PROHIBITED.

		NAME	TITLE: Mounting Plate Installation	
DRAWN	G. Williamson			
Check	I. Edmonds			
MATERIAL:			SIZE A	DWG. NO. MPI3-04
			Don't scale	REV. 03
			Sheet 1 of 1	